

Prosigns, Q codes and abbreviations

The shorthand operators send. A prosign is sent as one character, with no gap between its letters.

Prosigns

SOS		International distress signal	
AR		End of message	
AS		Wait / stand by	
BT		Break between sections	
SK		End of contact	
KN		Go ahead, named station only	
CT		Attention / starting signal	
SN		Understood	
HH		Error — start again	
K		Invitation to transmit (over)	

Q codes

QRL	Is this frequency in use?
QRM	I have interference
QRN	I am troubled by static
QRO	Increase power
QRP	Decrease power
QRQ	Send faster
QRS	Send more slowly
QRT	Stop sending
QRV	I am ready
QRZ	Who is calling me?
QSB	Your signal is fading
QSL	I acknowledge receipt
QSO	A two-way contact
QSY	Change frequency
QTH	My location is...

Abbreviations

CQ	Calling any station
DE	From (this is)
K	Over — go ahead
R	Roger — received
RST	Signal report
73	Best regards
88	Love and kisses
TNX	Thanks
UR	Your / you are
ES	And
PSE	Please
AGN	Again
OM	Old man (any operator)
WX	Weather
HI	Laughter

How the timing works

A dit is one unit. A dah is three units.
Gaps: one unit inside a letter, three between letters, seven between words.
At 20 WPM one unit is 60 ms. Speed changes the unit, never the ratios.